

PhyBOARD-WEGA-AM335x Linux Quickstart PD14.1-rc1

This Quickstart provides you with the tools and know-how to install and work with the Linux Yocto Board Support Package (BSP) for the phyBOARD-WEGA-AM335x kit. This Quickstart shows you how to do everything from installing the appropriate tools and source, to building custom kernels, to deploying the OS, to exercising the software and hardware. Please refer to the phyCORE-AM335x Hardware Manual for specific information on SOM-level features such as jumper configuration, memory mapping and pin layout for the phyCORE-AM335x System on Module (SOM). Additionally, gain access to the SOM, mapper board, and baseboard schematics for the phyBOARD-WEGA-AM335x by registering at the following: <http://phytec.com/support/registration/>.

- [Requirements](#)
 - [Hardware](#)
 - [Software](#)
- [Getting Started](#)
 - [Connector Interfaces](#)
 - [Booting the Pre-built Images](#)
- [Development Host Setup](#)
 - [Packages](#)
 - [Server Setup](#)
 - [TFTP](#)
 - [NFS](#)
 - [Samba](#)
- [Building the BSP](#)
 - [Download the BSP Meta Layers](#)
 - [Start the Build](#)
 - [Images](#)
 - [Build Time Optimizations](#)
- [Creating a Bootable SD card](#)
- [Boot Configurations](#)
 - [Selecting Boot Modes](#)
 - [Basic Settings](#)
 - [Expansion Board Settings](#)
 - [Network Settings](#)
 - [Saving Configurations](#)
 - [Boot Options](#)
- [Flashing Images](#)
 - [Barebox](#)
 - [Kernel](#)
 - [Root Filesystem](#)

Requirements

The following system requirements are necessary to successfully complete this Quickstart. Deviations from these requirements may suffice, or may have other workarounds.

Hardware

- phyBOARD-WEGA-AM335x (Part No. PB-00802)
- Evaluation Module (Part No. PEB-EVAL-01)
- Serial Cable (RS-232) - Not included
- Ethernet cable - Not included
- Power source - Not included. There are two power options for the phyBOARD-WEGA, the board can be populated with a two-pin phoenix connector which uses a 5V power supply, or come with the Power Module 12-24V (PEB-POW-01) which uses a 12/24V power supply. The 2-pin phoenix connector included can be used to connect the power input of the phyBOARD-WEGA to a lab power supply or Wall Adapter. Wall Adapter solutions are orderable through PHYTEC for the 5V version (LQP-5V1.5A-Adapter-P) and 12-24V version (LQP-12V1.25A-Adapter-P).

Software

- A modern GNU/Linux Operating host system either natively or via a virtual machine:

- Ubuntu 14.04 LTS 64-bit recommended. Other distributions will likely work, please note that some setup information as well as OS-specific commands and paths may differ.- If using a virtual machine, VMWare Workstation, VMWare Player, and VirtualBox are all viable solutions.

- Root access to your Linux Host PC. Some commands in the Quickstart will not work if you don't have sudo access (ex. package installation, formatting SD card).
- At least 40-50GB free on target build partition.
- SD card reader operational under Linux.

- If you do not have SD card access under Linux then formatting, copying the bootloader, and mounting the root file system on an SD card will not be possible.


- Active Internet connection

Getting Started

This section is designed to get the board up-and-running with pre-built images.

Connector Interfaces

Use the following as a reference for the connector interfaces on the phyBOARD-WEGA-AM335x that will be used in this Quickstart.



Booting the Pre-built Images

The section was designed to show you how to boot the phyBOARD-WEGA-AM335x with the pre-built demo images.

1. Insert a bootable SD card into the microSD card slot on the underside of the baseboard. Since the default boot mode for the PD14.1-rc1 release loads the kernel and root filesystem from the Barebox bootsource selected, configure the board to boot from SD/MMC ([Selecting Boot Modes](#)). A bootable SD card with *barebox.bin*, *MLO*, *zImage*, *zImage-am335x-wega-rdk.dtb*, and *phytec-hwbringup-image-phyboard-wega-am335x-1.tar.gz* extracted on the SD card is required. Instructions for creating an SD card are provided in the [Creating a Bootable SD card](#) section of the Quickstart.
2. Connect the serial cable from a free serial port on your host PC to the DB9 connector labelled UART0 on the module PEB-EVAL-01. This is the UART0 communication channel with the phyBOARD-WEGA-AM335x at RS-232 levels.
3. Connect the Ethernet cable from the Ethernet connector Eth0 to your network hub, router, or switch. If you do not have an Ethernet connection you can postpone this step, Linux will boot without the need for Ethernet connectivity but having the connection will significantly reduce your boot time.
4. Start your favorite terminal software (such as Minicom or TeraTerm) on your host PC and configure it for 115200 baud, 8 data bits, no parity, and 1 stop bit (8n1) with no handshake.
5. Plug the power supply into the power connector on the phyBOARD-WEGA. You will instantly see the red power LED D58 light up. You will also start to see console output on your terminal window. If everything was done correctly the board should boot completely into Linux, arriving at *aroot@phyboard-wega-am335x-1* prompt. The default login account is *root* with an empty password. Note that the first time the board is booted it will takes a little while for the SSH server to generate new keys. Subsequent boots should be faster.

```

COM1:115200baud - Tera Term VT
File Edit Setup Control Window Help
[ 2.919336] libphy: 4a101000.mdio: probed
[ 2.923571] davinci_mdio 4a101000.mdio: phy[0]: device 4a101000.mdio:00, driver SMSC LAN8710/LAN872
[ 2.932441] davinci_mdio 4a101000.mdio: phy[1]: device 4a101000.mdio:01, driver SMSC LAN8710/LAN872
[ 2.944090] Detected MACID = 20:cd:39:fe:f7:e2
[ 2.950710] cpsw: Detected MACID = 20:cd:39:fe:f7:e4
[ 2.959033] rtc-m41t80 0-0068: setting system clock to 2015-02-12 20:04:06 UTC (1423771446)
[ 2.979409] kjournald starting. Commit interval 5 seconds
[ 3.003655] EXT3-fs (mmcblk0p2): using internal journal
[ 3.009251] EXT3-fs (mmcblk0p2): mounted filesystem with ordered data mode
[ 3.016628] UFS: Mounted root (ext3 filesystem) on device 179:2.
[ 3.024485] devtmpfs: mounted
[ 3.028501] Freeing unused kernel memory: 396K (c0806000 - c0869000)
INIT: version 2.88 booting
Starting udev
[ 3.734213] udevd[1508]: starting version 182
[ 4.586718] PM: request_firmware failed
[ 4.601720] cryptodev: driver 1.6 loaded.
[ 6.605107] tlw320aic3x-codec 0-0018: ASoC: DAPM unknown pin MONO_LOUT
[ 6.614314] davinci_evm sound_iface.5: tlw320aic3x-hifi <-> 48038000.mcasp mapping ok
[ 6.699069] davinci_evm sound_iface.5: ASoC: no sink widget found for Speaker
[ 6.706893] davinci_evm sound_iface.5: ASoC: Failed to add route SPOP -> direct -> Speaker
[ 6.715797] davinci_evm sound_iface.5: ASoC: no sink widget found for Speaker
[ 6.723395] davinci_evm sound_iface.5: ASoC: Failed to add route SPOM -> direct -> Speaker
ALSA: Restoring mixer settings...
INIT: Entering runlevel: 5
Configuring network interfaces... [ 7.735726] net eth0: initializing cpsw version 1.12 (0)
[ 7.744393] net eth0: phy found : id is : 0x7c0f1
[ 7.756126] 8021q: adding VLAN 0 to HW filter on device eth0
[ 7.824118] net eth1: initializing cpsw version 1.12 (0)
[ 7.833058] net eth1: phy found : id is : 0x7c0f1
[ 7.841676] 8021q: adding VLAN 0 to HW filter on device eth1
done.
Starting OpenBSD Secure Shell server: sshd
done.
Starting syslogd/klogd: done

Poky (Yocto Project Reference Distro) 1.7 phyboard-wega-am335x-1 /dev/tty00

phyboard-wega-am335x-1 login: root
root@phyboard-wega-am335x-1:~#

```

Troubleshooting:

Not seeing any output on the console?

- Check that you have setup the terminal software correctly per step 4.
- Flash the release images from the PHYTEC FTP by creating a bootable SD/MMC card ([Creating a Bootable SD card](#)), then configure the board to boot from SD/MMC ([Selecting Boot Modes](#)).

Development Host Setup

The following notes assume a Ubuntu 14.04 64-bit build machine.

Packages

Yocto development requires certain packages to be installed. Run the following commands to ensure you have the packages installed:

```
sudo apt-get install gawk wget git-core diffstat unzip texinfo \
    gcc-multilib build-essential chrpath socat \
    libstdc++12-dev xterm
```

Note:

The above is the recommended package installation for phyBOARD-WEGA development on a Ubuntu 14.04 LTS Linux distribution. For a breakdown of the packages as well as a list of packages required for other Linux distributions, see the "Required Packages for the Host Development System" section in the Yocto Project Reference Manual: <http://www.yoctoproject.org/docs/1.7/ref-manual/ref-manual.html#required-packages-for-the-host-development-system>

Verify that the preferred shell for your Host PC is *bash* and not *dash*:

```
sudo dpkg-reconfigure dash
# Respond "No" to the prompt asking "Install dash as /bin/sh?"
```

Download and install the **repo** tool. This tool is used to obtain Yocto source from Git.

```
cd /opt
sudo mkdir bin

# /opt/ directory has root permission, change the permissions so your user account can access this folder. In the
following replace <user> with your specific username
sudo chown -R <user>: bin

cd bin
curl http://commondatastorage.googleapis.com/git-repo-downloads/repo > ./repo
#add directory that contains repo to your path
chmod a+x repo
```

Add the *repo* directory in your PATH, using **export** from the command line or permanently by including it in *.bashrc*:

```
PATH=/opt/bin/:$PATH
```

Server Setup

The following steps describe the setup for TFTP, NFS, and Samba servers. Server setup is not required for working with the phyBOARD-WEGA, however they will significantly reduce time and are highly recommended during the building and development phase.

TFTP

TFTP is a "trivial" file transfer protocol used to transfer individual files across a network. Setting up a TFTP server on your Linux Host PC will allow you to exchange files with the target board. Some examples where this will be advantageous include:

- Modifying and doing development on the Linux kernel. Barebox can be configured to remotely boot the kernel so you have access to the latest build without needing to continually reflash the target board.
- Updating images from the bootloader. Transferring files over a network in Barebox is an alternative to using an SD card which eliminates some time consuming steps such as formatting an SD card.
- Individual file transfer to the root filesystem. When Linux has been fully booted you may want to copy a specific file from your Host PC to the target board (images, application executables).

Install the TFTP server on your Host PC:

```
sudo apt-get install tftpd-hpa
```

Specify a folder where the files will reside on your Host PC by replacing the folder path for *TFTP_DIRECTORY* with whatever folder you wish to use as your TFTP file storage location, or leave the folder as the default.

```
sudo gedit /etc/default/tftpd-hpa

# /etc/default/tftpd-hpa

TFTP_USERNAME="tftp"
TFTP_DIRECTORY="/var/lib/tftpboot"
TFTP_ADDRESS="0.0.0.0:69"
TFTP_OPTIONS="--secure"
```

If you made any changes to the settings of the TFTP server, you need to restart it for them to take effect.

```
sudo restart tftpd-hpa
```

If you would like to grant every user on the system permission to place files in the TFTP directory, use the following command, replacing *<TFTP_DIRECTORY>* with your chosen location.

```
sudo chmod ugo+rw <TFTP_DIRECTORY>
```

Files in the *<TFTP_DIRECTORY>* on your Host PC can now be accessed from another machine on the same network such as the target board by simply using the IP address of the Host PC. Take note of this IP address, in a typical wired connection this will be *inet addr* listed under *eth0*.

```
ifconfig
```

NFS

A network filesystem (NFS) server gives other systems the ability to mount a filesystem stored on the Host PC and exported over the network. Setting up an NFS server on your Linux Host PC gives you access to the target boards root filesystem which will allow you to quickly test applications and evaluate different filesystem setups for the target board. That is, the root filesystem for the phyBOARD-WEGA will actually be located on the remote host Linux machine. This enables easy access and modifications to the root filesystem during development.

Install the NFS server on your Host PC:

```
sudo apt-get install nfs-kernel-server
```

Exported filesystems are designated in the "/etc/exports" file and allow you to choose both the directory to be exported and many settings for accessing the exports. Below is an example for exporting a folder called "nfs_export-ex" located in a user's home directory.

```
sudo gedit /etc/exports
# /etc/exports
/home/<user>/nfs_export-ex *(rw,sync,no_root_squash,no_subtree_check)
```

The options (rw, sync, no_root_squash, no_subtree_check) for this folder are essential in setting up the NFS export correctly. For more information on additional options, refer to the man page for 'exports'.

- rw enables

read and write access when the directory is mounted

- sync

tells the file-system to handle local access calls before remote access

- no_root_squash

allows root access when mounting the file-system

- no_subtree_check

reduces the number of checks the server must make to ensure that an exported sub-directory is within an exported tree and also enables access to root files in conjunction with no_root_squash

After modifying this file, in order to mount the directories as an NFS, you must force the NFS server to export all of the directories listed in "/etc/exports".

```
sudo /usr/sbin/exportfs -va
```

Samba

Samba servers are an excellent way to access a Linux file-system on a Windows machine via a network connection. Using a Samba server, it is quick and easy to transfer files between systems.

To install a Samba server, use the following command:

```
sudo apt-get install samba
```

Before the Samba share can be mounted on another machine it's necessary to modify the configuration file to allow write access and access to home directories. Start by editing the "/etc/samba/smb.conf" file.

```
sudo gedit /etc/samba/smb.conf
```

Inside this file there are four specific things that need to be uncommented (remove the ';' at the beginning of the line) to enable the sharing of home folders and write access. Below is the section that must be modified:

```
===== Share Definitions =====

# Un-comment the following (and tweak the other settings below to suit)
# to enable the default home directory shares. This will share each
# user's home directory as \\server\username
[homes]
; comment = Home Directories
; browseable = yes

# By default, the home directories are exported read-only. Change the
# next parameter to 'no' if you want to be able to write to them.
; read only = no
```

The outcomes after the changes are made follow:

```
===== Share Definitions =====

# Un-comment the following (and tweak the other settings below to suit)
# to enable the default home directory shares. This will share each
# user's home directory as \\server\username
[homes]
    comment = Home Directories
    browseable = yes

# By default, the home directories are exported read-only. Change the
# next parameter to 'no' if you want to be able to write to them.
    read only = no
```

Note:

It might also be necessary to change the *workgroup* line to match the workgroup for your machine.

To apply the changes, the next step is to restart all Samba-related processes.

```
sudo restart smbd
sudo restart nmbd
```

Lastly, each user needs to have a password enabled to be able to use the Samba server. There are no rules for this password. The simplest method for choosing this password is to make it the same as the UNIX user's password, but it is not a requirement. After typing in the command below, you will be prompted to enter the password for the specified user.

```
sudo smbpasswd -a <user>
```

As mentioned in the configuration file, the samba share can be connected by accessing "`\\<host machine ip>\\<user>`" by either mounting a network share or using Windows explorer to navigate to it.

Building the BSP

Create a directory which will house your BSP development. In this example the BSP directory is `/opt/PHYTEC_BSPs/`. This is not a requirement and if another location is preferred (ex. `~/PHYTEC_BSPs`) feel free to modify. We recommend using `/opt` over your HOME directory to avoid errors attributed to `~` syntax as well as the `sudo` requirement for the root filesystem and automation package building. We also recommend creating a package download directory (`yocto_dl`) separate from the yocto tree (`yocto_ti`), as it makes resetting the build environment easier and subsequent build times much faster.

```
sudo mkdir /opt/PHYTEC_BSPs
cd /opt/

# /opt/ directory has root permission, change the permissions so your user account can access this folder. In the
following replace <user> with your specific username
sudo chown -R <user>: PHYTEC_BSPs

cd PHYTEC_BSPs
mkdir yocto_ti
mkdir yocto_dl
cd yocto_ti
export YOCTO_DIR=`pwd`
```

At this point you will now be able to navigate to the Yocto directory using the `$YOCTO_DIR` environment variable.

Download the BSP Meta Layers

Download and run the init script `phyLinux`. This script will use the `repo` tool to manage the various git repositories used in this BSP. `Repo` will automatically be detected by `phyLinux` if it is found in the `PATH`. During the execution of the script, you need to choose your processor platform, BSP release and hardware. The following are the available machine configurations:

- **phyboard-maia-am335x-1**: PB-00702-002
- **phyboard-wega-am335x-1**: PB-00802 with HDMI Adapter PEB-AV-01
- **phyboard-wega-am335x-2**: PB-00802 with GLYN Display AV-Adapter PEB-AV-02
- **phycore-am335x-1**: PCM-051-12102F0C.A1/PCM-953 (Standard Rapid Development Kit)
- **phycore-am335x-2**: 1GiB RAM, 1GiB NAND SOM variant with PCM-953 Carrier Board
- **phyflex-am335x-1**: PFL-A-03-12113F8l.A1/PBA-B-01 (Standard phyFLEX i.MX6 Rapid Development Kit)

The rest of the Quickstart assumes that the standard *phyboard-wega-am335x-1* is used, although the other phyBOARD-WEGA configurations may be used as well.

```
cd $YOCTO_DIR
wget ftp://ftp.phytec.de/pub/Software/Linux/Yocto/Tools/phyLinux
chmod +x phyLinux

# You can provide the SoC platform, BSP release, and hardware as arguments:
./phyLinux init -p am335x -r PD14.1-rc1 -m phyboard-wega-am335x-1

# Or simply run the init script and you will be prompted to choose the desired settings from a list of options
./phyLinux init
```

After the configuration is set up, you can view the current settings by running:

```
./phyLinux info
```


Start the Build

Run the Yocto build directory setup:

```
cd $YOCTO_DIR
MACHINE=phyboard-wega-am335x-1 source sources/poky/oe-init-build-env build
```

Add the the new download directory to build/conf/local.conf:

```
DL_DIR ?= "/opt/PHYTEC_BSPs/yocto_dl"
```

The setup is complete and you now have everything to complete a build. The following will start a build from scratch including installation of the toolchain as well as barebox, Linux kernel, and root filesystem images.

```
cd $YOCTO_DIR/build
MACHINE=phyboard-wega-am335x-1 bitbake --continue phytec-hwbringup-image
```

Note:

If the package fetch fails, you will need to manually download the linuxptp IEEE 1588 stack to \$DL_DIR (<http://sourceforge.net/projects/linuxptp/files/>). Once you've downloaded the archive (e.g. linuxptp-1.3.tgz), you will need to create a "done" file so fetch doesn't delete the file and try to refetch it:

```
cd yocto_dl
touch linuxptp-1.3.tgz.done
```

Because of a race condition in the build system, sometimes barebox or the linux kernel will not get configured correctly and the system will not boot. The fix will be available in the next release; in the meantime there is a workaround for this which only needs to be done after the very first build:

- Rebuild barebox after the image has been generated:

```
bitbake -c cleanall barebox barebox-ipl linux-ti && bitbake phytec-hwbringup-image -c rootfs -f
```

Images

All images generated by bitbake are deployed to `$YOCTO_DIR/build/deploy/images/phyboard-wega-am335x-1`:

- **SD Image:** phytec-hwbringup-image-phyboard-wega-am335x-1.sdimg-phy
- **Bootloader:** barebox.bin, MLO
- **Kernel:** zImage
- **Kernel device tree file:** zImage-am335x-wega-rdk.dtb
- **Root Filesystem:** phytec-hwbringup-image-phyboard-wega-am335x-1.tar.gz

The Linux kernel source is located in: `$YOCTO_DIR/build/tmp/work/phyboard_wega_am335x_1-poky-linux-gnueabi/linux-ti/3.12.24-phy1-r0/git/`. The device tree file to modify within the linux kernel source is: `arch/arm/boot/dts/am335x-wega-rdk.dts` and its dependencies.

Build Time Optimizations

The build time will vary depending on the package selection and Host performance. Beyond the initial build, after making modifications to the BSP, a full build is not required. Use the following as a reference to take advantage of optimized build options and reduce the build time.

To rebuild Barebox:

```
bitbake barebox -f -c compile && bitbake barebox
```

To rebuild the Linux kernel:

```
bitbake linux-ti -f -c compile ; bitbake linux-ti
```

The Yocto project's Bitbake User Manual provides useful information regarding build options: <http://www.yoctoproject.org/docs/1.7/bitbake-user-manual/bitbake-user-manual.html>

Creating a Bootable SD card

The process requires an SD card reader operational under Linux to format and access the Linux partition of the card. If you do not have SD card access under Linux then copying the bootloader and mounting the root filesystem on SD/MMC card will not be possible.

1. Determine the SD card device name

- The SD card device name is of the form /dev/sd[b|c|d|e]. Run the following without and with the SD card connected:

```
ls /dev/sd*
```

- The device that appeared on the call to ls with the SD card but not the call without is the SD card device.

2. Unmount all partitions of the SD card, using the SD card device name from Step 1:

```
umount /dev/sd[b|c|d|e]*
```

3. Load the sd-card image onto the SD card from the linux command line. This will format the /media/boot and /media/root partitions, as well as add Barebox, the kernel image, and the root filesystem to the card:

```
sudo dd if=phytec-hwbringup-image-phyboard-wega-am335x-1.sdimg-phy of=/dev/sd[b|c|d|e] bs=1MB
```

Once the SD card has been formatted, you may update the kernel, root filesystem, and barebox individually as well:

Kernel

4. If modifying the kernel, remove the existing linuximage and device tree binary files:

```
rm -rf /media/boot/*
```

5. Load the new Linux kernel and device tree binary to the SD Card. Note that the default bootloader environment is configured to recognize "linuximage" and "oftree" as the kernel and dts respectively:

```
cp zImage /media/boot/linuximage; sync
cp zImage-am335x-wega-rdk.dtb /media/boot/oftree; sync
```

Root Filesystem

6. If modifying the root filesystem, remove the existing:

```
sudo rm -rf /media/rootfs/*
```

7. Load the new filesystem to the SD Card:

```
sudo tar -zxvf phytec-hwbringup-image-phyboard-wega-am335x-1.tar.gz -C /media/root/; sync
```

Bootloader

```
cp barebox.bin /media/boot/; sync
cp MLO /media/boot/; sync
```

Note:

Unmount each partition before removing the SD Card:

```
umount /media/boot /media/rootfs
```


Additionally, if you plan on using the SD/MMC card to flash images, copy the files to the /boot partition. Since the /boot partition is FAT32 file copying can be handled using a Windows machine and a Linux machine is not required.

Boot Configurations

Selecting Boot Modes

The bootloader, one of the key software components included in the BSP, completes the required hardware initializations to download and run operating system images. The boot mode determines the location of the primary bootloader. The way the bootmode is selected depends on the revision of the carrier board. This is printed on the board, and is either 1405.0 or 1405.1.

If using 1405.0, short pin 8 of X70 (X_LCD_D2) to pin 13 of X71 (VCC3v3) as shown in the picture below:



Otherwise, if you are using 1405.1, set the switch S1 on the baseboard to ON to force booting from SD card.



Basic Settings

After application of power, approximately three seconds are allotted for the user to hit any key which will halt autoboot and enter Barebox.

```
COM6:115200baud - Tera Term VT
File Edit Setup Control Window Help

barebox 2014.10.0-PD14.1-rc1-dirty #1 Tue Jan 13 10:56:37 PST 2015

Board: Phytec phyCORE AM335x
omap-hsmmc 48060000.mmc: registered as 48060000.mmc
booting from MMC
mmc0: detected SD card version 2.0
mmc0: registered mmc0

barebox 2014.10.0-PD14.1-rc1-dirty #1 Tue Jan 13 10:56:55 PST 2015

Board: Phytec phyCORE AM335x
cpsw 4a100000.ethernet: detected phy mask 0x5
mdio_bus: miibus0: probed
eth0: got preset MAC address: d0:ff:50:33:20:6c
m25p80 m25p800: s25s1064p (8192 Kbytes)
i2c-omap 44e0b000.i2c: bus -1 rev0.11 at 400 kHz
omap-hsmmc 48060000.mmc: registered as 48060000.mmc
mmc0: detected SD card version 2.0
mmc0: registered mmc0
nand: ONFI param page 0 valid
nand: ONFI flash detected
nand: NAND device: Manufacturer ID: 0x2c, Chip ID: 0xdc (Micron MT29F4G08ABDAH4), 512MiB, page size: 2048, OOB size: 64
netconsole: registered as netconsole-1
malloc space: 0x8ff00000 -> 0x9fdfffff (size 255 MiB)
running /env/bin/init...

Hit m for menu or any other key to stop autoboot: 3

type exit to get to the menu
barebox@Phytec phyCORE AM335x:/
```

Note:

help is a useful tool in Barebox to show available commands and usage.

Use the Barebox configuration files to modify environment variables, select boot settings, and setup networking parameters.

Expansion Board Settings

This BSP supports enabling and disabling various expansion boards that may be used along with the carrier board via the bootloader. This functionality allows for certain pin configurations to be added or removed from the device tree without needing to recompile the kernel. Please note that not all of these will be compatible with your specific board.

- To view the available expansion boards:

```
barebox@Phytec phyCORE AM335x:/ ls /env/expansions/
.
am335x-phytec-lcd-018-pba-b-01      am335x-phytec-lcd-018-pba-c-01
am335x-phytec-lcd-018-pcm-953      am335x-phytec-lcd-018-peb-av-02
am335x-wega-peb-av-01              am335x-wega-peb-eval-01
```

Enable an expansion board by adding it to /env/config-expansions:

```
edit /env/config-expansions
```

- You should see something similar to the following. By default, Barebox built with the phyBOARD-WEGA-AM335x configures the kernel to enable the HDMI adapter PEB-AV-01 as well as the user leds and buttons on the PEB-EVAL-01 expansion:

```
#!/bin/sh

global linux.bootargs.dyn.video

. /env/expansions/am335x-wega-peb-av-01
. /env/expansions/am335x-wega-peb-eval-01

global.linux.bootargs.dyn.video="video=HDMI-A-1:1024x768-32@60"
```

Note:

The 3.12 kernel used by this BSP does not support device tree overlays.

Network Settings

You can check the target's network settings by running the following:

```
devinfo eth0
```

The `ethaddr` variable is the MAC id of the target. This is a pre-programmed value which is read from the EEPROM and matches the sticker on the SOM. To modify any of the network settings, type:

```
edit /env/network/eth0
```

You should see something similar to the following, modify the variables to specify your network configuration for ETH0:

```
ipaddr=###.###.###.###
netmask=###.###.###.###
gateway=###.###.###.###
serverip=###.###.###.###
```

- **ipaddr**

A dedicated IP address for the SOM. This is crucial if TFTP will be used for updating the device's images at any point.

- **netmask**

Netmask for the network: typically 255.255.255.0. This is only necessary if the TFTP directory is located on another network.

- **gateway**

Gateway IP for the network. This is only necessary if the TFTP directory is located on another network.

- **serverip**

IP address of the host or another machine. serverip corresponds to where the TFTP directory, if it exists, is located.

Saving Configurations

From any of the Barebox scripts, return to the Barebox prompt by pressing **CTL+D** to apply changes or **CTL+C** to cancel. To retain changes, at the Barebox prompt save the environment.

```
saveenv
```

Boot Options

The target can be booted from on-board media or from a development host via network. In our standard configuration, the PD14.1-rc1 BSP release loads the kernel and root filesystem from the bootsource selected in the hardware.

For booting via network, the development host is connected to the phyCORE-AM335x with a serial cable and via Ethernet; the embedded board boots into the bootloader, then issues a TFTP request on the network and boots the kernel from the TFTP server on the host. Then, after decompressing the kernel into RAM and starting it, the kernel mounts its root filesystem via the NFS server on the host. This method is especially useful for development purposes as it provides a quick turnaround while testing the kernel and root filesystem.

Stand-Alone NAND Boot

To use the target stand-alone, the kernel and root filesystem have to be made persistent in the on-board media of the phyBOARD-WEGA. This is done by default in the kit, however if the kernel and root filesystem are not available in the on-board media or you would like to update them, refer to [Flashing Images](#) for information on flashing images.

When set in the dipswitch ([Selecting Boot Modes](#)), the phyBOARD-WEGA is configured by default to boot the kernel and mount the root filesystem from flash. By simply resetting or power cycling the board the target will boot into Linux.

The nand boot entry can also be run from the Barebox shell:

```
boot nand
```

Remote Boot

The network-remote boot variant is intended to be used during development because of the frequent need to rebuild the Linux kernel and root filesystem. TFTP and NFS accelerate the development process. Reflashing the newest kernel and root file system to the SOM after every new build would be very cumbersome and time consuming. All that is needed is an Ethernet connection and a network aware bootloader which can fetch the kernel from a TFTP server.

Restart the board and stop autoboot to go into the Barebox shell. Run the command:

```
boot net
```

Stand-Alone SD/MMC card Boot

The SD/MMC card boot variant is an alternative stand-alone boot option. All that is needed is a properly formatted (see the [Creating a Bootable SD card](#) section of the Quickstart) SD/MMC card

Restart the board and stop autoboot by pressing m. You'll get a menu:

```
Main menu
  1: Boot default
  2: Detect bootsources
  3: Settings
  4: Save environment
  5: Shell
  6: Reset
```

Press 2 and then the Enter key to descend into "Detect bootsources". From this menu you can select the interface in which to boot from. Press 3 and then the enter key.

The SD/MMC card boot entry can also be run from the Barebox shell:

```
boot mmc
```

Custom Boot

You may have custom boot requirements that are not covered by the four available boot files (nand, net, mmc, spi). If this is the case you can create your own custom boot entry specifying the kernel and root filesystem location.

- In Barebox, create your own boot entry, for example named *custom*:

```
edit /env/boot/custom
```

- Use the following template to specify the location of the Linux kernel and root filesystem. Please note that the text in <> such as *<kernel_loc_bootm.image>*, *<rootfs_loc_dyn.root>*, and *<nfs_root_path>* are intended to be replaced with user specified values.

```
#!/bin/sh

global.bootm.image="<kernel_loc_bootm.image>"
global.bootm.oftree="<dts_loc_bootm.oftree>"

nfsroot="<nfs_root_path>"
bootargs-ip
/env/config-expansions

global.linux.bootargs.dyn.root="<rootfs_loc_dyn.root>"
```

- **<kernel_loc_bootm.image>**

Specifies the location of the Linux kernel image/dev/[nand0.kernel.bb](#) - To boot the Linux kernel from NAND\$(path)/linuximage - To boot the Linux kernel via TFTP/boot/linuximage - To boot the Linux kernel from SD/MMC card

- **<dts_loc_bootm.ofmtree>**

Specifies the location of the device tree binary/`dev/nand0.ofmtree.bb` - To boot the device tree binary from NAND\${path}/ofmtree - To boot the device tree binary via TFTP/boot/ofmtree - To boot the device tree binary from SD/MMC card

- **<rootfs_loc_dyn.root>**

Specifies the location of the root filesystem
`root=ubi0:root ubi.mtd=root rootfstype=ubifs` - To mount the root filesystem from NAND
`root=/dev/nfs nfsroot=$nfsroot,vers=3,udp rw consoleblank=0` - To mount the root filesystem via NFS
`root=/dev/mmcblk0p2 rootfstype=ext3 rootwait` - To mount the root filesystem from SD/MMC card

- **<nfs_root_path>**

Only required if mounting the root filesystem from NFS. Replace with the following:
`nfsroot="/home/${global.user}/nfsroot/${global.hostname}"`

Once complete with file modifications exit the editor using **CTRL+D**. Save the environment:

```
saveenv
```

To run your custom boot entry from the Barebox shell:

```
boot custom
```

Default Boot

The phyBOARD-WEGA is configured by default to boot the kernel and mount the root filesystem from the bootsource set for Barebox in the dipswitch ([Selecting Boot Modes](#)). This default setting can be changed by adding or modifying the `global.boot.default` environment variable.

```
edit /env/config-board
```

Comment out the if else statements which set the boot sequence depending on the Barebox bootsource, and add the `global.boot.default` variable to set to the desired boot source. This variable can be set to any of the entries in `/env/boot`. For example, to set the default boot configuration to `net,global.boot.default` should be set in the following way:

```
global.boot.default=net
```

Exit the editor by **CTRL+D** and save the environment (saveenv). On a reset or power cycle the new default boot source will take affect. Similarly it will be used in the Barebox shell when executing the following:

```
boot
```

Flashing Images

The phyBOARD-WEGA Development Kit is delivered with a pre-flashed bootloader. The following instructions for flashing images from TFTP or SD card will be useful if you want to:

- Flash images because NOR is empty
- Upgrade to a new release
- Use custom built images

The images to be flashed will need to be copied to the exported TFTP directory or the `/boot` partition of a properly formatted SD card as described in the [Creating a Bootable SD card](#) section of the Quickstart.

After making all required connections, power on the board and enter Barebox:

- If flashing from TFTP, connect an Ethernet cable from the Ethernet connector `ETH0` on the board to your network hub, router, or switch.
- If flashing from SD card, insert a correctly formatted microSD card into the SD/MMC card slot connector on the underside of the Carrier Board.
- Connect a serial RS-232 cable from a free port on your Host PC to the connector UART0 on the Carrier Board.
- Start your favorite terminal software (Windows: PuTTY or TeraTerm; Linux: Minicom) on your Host PC and configure it for 115200 baud, 8 data bits, no parity, and 1 stop bit (8n1).
- Power on your board by connecting the wall adapter to the Carrier Board.
- After application of power, within approximately three seconds, hit any key to halt autoboot and enter Barebox. If an Ethernet cable is connected and the network has been configured, TFTP will automount to `/mnt/tftp`. If an SD card was inserted and Barebox was booted from MMC, the `/boot` partition will automount to `/boot`.

Note:

If booting the bootloader from a source other than MMC, the `/boot` partition of the SD/MMC card will not automatically mount. To mount, execute the following commands each time you stop autoboot from Barebox or add them to `/env/init/automount` so this is done automatically:

```
mkdir -p boot
mount /dev/mmc0.0 boot
```

If flashing from TFTP, additional setup to configure the Barebox environment variables to meet your network environment and development host settings is required. The current network settings can be checked in `/env/network/eth0`.

If you need to change you network configuration, type:

```
edit /env/network/eth0
```

Edit the settings as described in the [Network Configuration](#) section of the Quickstart. Save the environment and reboot the board, this will automount your tftp server at boot to `/mnt/tftp`.

Barebox

If you would like to upgrade, have custom Barebox requirements, or are interested in seeing the version you built in action, follow the steps below:

`barebox.bin` should be copied to your TFTP exported directory or the `/boot` partition of the SD card depending on your chosen flashing procedure.

- Copy the new Barebox from your tftp-server or SD card into the module's RAM:

Method: TFTP

```
cp /mnt/tftp/barebox.bin .
```

Method: SD/MMC

```
cp /boot/barebox.bin .
```

- Store the Barebox into NAND Flash:

```
erase /dev/nand0.barebox.bb
cp barebox.bin /dev/nand0.barebox.bb
```

- Copy the MLO and barebox.env into the module's RAM in the same manner as barebox.bin. To store the MLO in NAND Flash:

```
erase /dev/nand0.xload.bb
cp MLO /dev/nand0.xload.bb
```

- To restore the barebox environment in NAND Flash to the default environment:

```
erase /dev/nand0.bareboxenv.bb
```

Note:

If something goes wrong and you don't have a bootloader anymore on your module you need to boot from an SD card into Barebox (set the DIP-switch as stated in [Boot Configurations](#)) and then do the flashing. See the [Creating a Bootable SD card](#) section of this Quickstart for a description of how to create a bootable SD card.

Kernel

Placing the kernel into NAND Flash allows booting the system without the need for the TFTP hosted kernel image. This is the most common place to put the kernel in a stand-alone application. Normally development is done using a TFTP hosted kernel image until the configuration has become more stable and is unlikely to change frequently. Once stable, the kernel image can be moved to NAND Flash. This section assumes a Linux kernel with file name linuximage is available on the exported TFTP directory or /boot partition of the SD card depending on your chosen flashing procedure.

- Erase the area of NAND Flash reserved for the kernel image and device tree binary partitions:

```
erase /dev/nand0.kernel.bb
erase /dev/nand0.oftree.bb
```

- Copy the Linux kernel from your tftp-server or SD card and store it into the NAND Flash:

Method: TFTP

```
cp /mnt/tftp/linuximage /dev/nand0.kernel.bb
cp /mnt/tftp/oftree /dev/nand0.oftree.bb
```

Method: SD/MMC

```
cp /boot/linuximage /dev/nand0.kernel.bb  
cp /boot/oftree /dev/nand0.oftree.bb
```

Root Filesystem

Similar to the Linux kernel, placing the root filesystem into NAND Flash allows booting the system without the need for a remote connection to the NFS server. This section assumes a root filesystem of the form root.ubifs available on the exported TFTP directory or /boot partition of the SD card depending on your chosen flashing procedure. Note that you should not flash Linux's root filesystem into NAND the same way as you did with Linux kernel.

- Ubifs keeps erase counters within the NAND in order to be able to balance write cycles equally over all NAND sectors. So if there's already an ubifs on your module and you want to replace it with a new one, using erase and cp will also erase these erase counters, and this should be avoided. Instead, execute the following:

```
ubiformat /dev/nand0.root  
ubiattach /dev/nand0.root  
ubimkvol /dev/ubi0 root 0
```

- Copy the root filesystem from your tftp-server or SD card and store it into the NAND Flash:

Method: TFTP

```
cp /mnt/tftp/phytec-hwbringup-image-phyboard-wega-am335x-1.ubifs /dev/ubi0.root
```

Method: SD/MMC

```
cp /boot/phytec-hwbringup-image-phyboard-wega-am335x-1.ubifs /dev/ubi0.root
```